

ARL-PROP-TM-468

AR-006-058

4



DTIC FILE COPY

AD-A218 367

DEPARTMENT OF DEFENCE
DEFENCE SCIENCE AND TECHNOLOGY ORGANISATION
AERONAUTICAL RESEARCH LABORATORY
MELBOURNE, VICTORIA


Propulsion Technical Memorandum 468

COMPLEX DEMODULATION FOR BEARING FAULT DETECTION

by

I. M. HOWARD

Approved for public release



COMMONWEALTH OF AUSTRALIA 1989

OCTOBER 1989

90 02 23 120

DEPARTMENT OF DEFENCE
DEFENCE SCIENCE AND TECHNOLOGY ORGANISATION
AERONAUTICAL RESEARCH LABORATORY

Propulsion Technical Memorandum 468

COMPLEX DEMODULATION FOR BEARING FAULT DETECTION

by

I.M. HOWARD

SUMMARY

Vibration analysis using the high frequency resonance technique has been used successfully to detect incipient failure in rolling element bearings. This memo outlines a new method of obtaining the demodulated narrow band envelope of a bearing vibration signal from the high frequency resonant response. Previous techniques have used an analogue envelope where the raw analogue signal is bandpass filtered and enveloped before digitising. The method outlined in this document first digitises the vibration signal, performs a complex demodulation operation, then computes the envelope followed by its spectrum. Fault repetition frequencies can be identified in the demodulated spectrum of the high frequency resonant response.




(C) COMMONWEALTH OF AUSTRALIA 1989

POSTAL ADDRESS: Director, Aeronautical Research Laboratory,
P.O. Box 4331, Melbourne, Victoria, 3001, Australia

CONTENTS

Summary	
1.	Introduction 1
2.	Complex Demodulation..... 2
2.1	Digital Bandpass Filtering 2
3.	Experimental Verification..... 5
3.1	Bearing Vibration Test Rig 5
3.2	Experimental Results 5
3.3	Discussion..... 6
4.	Conclusion..... 6
5.	Acknowledgements..... 7
6.	References 7
Figures	
Document Data	
Distribution List	



Accession For	
NTIS GRA&I	<input checked="checked" type="checkbox"/>
DTIC TAB	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
By _____	
Distribution/	
Availability Codes	
Dist	Avail and/or Special
A-1	

1. INTRODUCTION

Incipient faults in rotating machines can be detected and diagnosed by the measurement and analysis of the vibration from the machine structure. A wide range of techniques, simple and complex, have been used in the past to detect changes in the operating condition of the machine from the vibration signature. For the detection of early failure in rolling element bearings, these have included spike energy, shock pulse, kurtosis and crest factor [1-5], and the high frequency resonance technique [6-11].

Some of these techniques have proved to be unsuccessful in certain instances. The difficulty is due to the fact that bearing faults often produce vibrations of low level which are hidden in the vibrations from other machine components, such as pumps and gears. The successful diagnostic techniques have concentrated on detecting the periodic impulses which occur when the damaged rolling elements come into contact with the other bearing elements.

In the case of defects on the bearing race elements, impacts will be generated each time a rolling element rotates past the defect. The repetition frequency of the impacts can be determined from the characteristic bearing frequency equations [4, 9]. In this regard, the high frequency resonance technique has shown significant promise in being able to discern not only the bearing condition, but the bearing element which contains the initial damage.

In the early stages of bearing failure, the impacts have a very high frequency content, >200 kHz being reported [7]. These impacts excite the various resonances of the bearing elements. By analysing the modulation about these structural resonances, the bearing impact frequencies caused by the repetitive rotation of the bearing elements over the damage can be determined.

In the past [6-11], the high frequency resonance technique has been implemented by first obtaining the analogue envelope of the band pass filtered vibration signal. The pass band is centred around a structural resonance. Some of the difficulties which have been reported in using this approach have concerned the design of the envelope detector [11]. Often a half or full wave rectifier is used followed by a smoothing circuit. The selection of these components, especially the time constant to achieve the correct decay rate of the envelope signal, is critical to the success of this technique.

In this memorandum, a digital process is presented for demodulating the vibration signal around a structural resonance, to obtain the envelope of the bearing vibration.

2. COMPLEX DEMODULATION

The demodulation of the bearing vibration signal can be performed digitally, giving a number of advantages compared with the analogue approach [11]. The major advantage is that the signal is demodulated by operations in the time domain only; no Fourier transform into the frequency domain is needed. Another advantage occurs in the filtering operation, where a simple low pass digital filter is required as opposed to a bandpass filter for the analogue approach. The flexibility in specifying the centre frequency of the structural resonance to be demodulated is also an advantage. For the digital process this is achieved by simply specifying the carrier frequency in software. For the analogue approach, the hardware filter characteristics require changing, although this could also be achieved in a software controlled system using the more expensive programmable filters.

2.1 Digital Bandpass Filtering

Complex demodulation of the structural resonance can be achieved digitally using heterodyning in the time domain [12-16]. The complete operation can be expressed as outlined below.

A vibration signal U from a rolling element bearing, and containing a response from at least one structural resonant frequency, can be assumed to have a frequency spectrum as shown in Figure 1. The measured vibration signal can be digitised by an analogue to digital converter at a fixed sampling frequency f_s . The Nyquist criterion requires that the maximum frequency content of the analogue signal should be limited to less than $f_s/2$.

Once sampled, the signal is no longer continuous and is a function of sample number rather than time. With N data points the sampled function U can be expressed as

$$\{ U \} = u(i T_s), \quad i=1 \dots N \quad (1)$$

where T_s is the sample interval. Demodulation of the vibration signal around the structural resonance shown in Figure 1 is obtained by heterodyning or frequency shifting the digitised vibration time signal. This is achieved by multiplying the signal by the complex exponential function

$$e^{-j2\pi f_o i T_s},$$

which produces a time domain signal shifted by frequency f_0 . The resulting heterodyned signal is then given by

$$v(iT_s) = u(iT_s) e^{-j2\pi f_0 iT_s}, i=1\dots N \quad (2)$$

which can be expanded to give,

$$= u(iT_s) \cos(2\pi f_0 iT_s) - ju(iT_s) \sin(2\pi f_0 iT_s).$$

This can be rewritten in terms of real and imaginary components to be,

$$\{V\} = v(iT_s) = a(iT_s) + jb(iT_s) \quad (3)$$

where $j = \sqrt{-1}$. In the frequency domain, the frequency shift is shown in Figure 2.

This signal is now complex, containing both real and imaginary parts. To obtain the complex demodulated vibration, this signal is now low pass filtered. Both real and imaginary components are filtered, using a digital, zero phase filter. A frequency domain representation of the filtered signal is shown in Figure 3.

Digital filtering can be seen as the convolution of the heterodyned signal with the impulse response of the zero phase filter. The resulting function $\{W\}$ is then given by,

$$\{W\} = \{V\} * \{H\}, \quad (4)$$

where $*$ denotes convolution and $\{H\}$ is the impulse response of the zero phase filter. This can be rewritten using the convolution integral,

$$\{W\} = \int_{-\infty}^{\infty} v(\tau) H(t-\tau) d\tau, \quad (5)$$

or in discrete terms

$$\{W\} = \sum_{k=1}^N v(kT_s) H((i-k)T_s), \quad (6)$$

The resulting function can then be expressed as,

$$w(iT_s) = c(iT_s) + jd(iT_s), i=1\dots N \quad (7)$$

separating out the real and imaginary components.

The complex signal can now be decimated in time by resampling at low frequency as the resulting signal $\{W\}$ contains only frequency components between $-f_a < f < f_a$. Decimation by a factor of say ten, can be used where the bandwidth of the filtered signal is less than one tenth of the bandwidth of the original time signal. The decimation of the time signal can be achieved by multiplying the complex time signal by a unit sampling sequence $\{G\}$. This can be defined using a unit sampling function $g(n)$ defined as

$$g(n) = \begin{cases} 0 & -\infty < n < \infty, \text{ except } n = 0 \\ 1 & n = 0 \end{cases}$$

The unit sample sequence $\{G\}$ for resampling the analytic signal $\{W\}$ with a sampling period T_d , can now be defined as,

$$\{G\} = \sum_{k=-\infty}^{\infty} g(iT_s - kT_d) \quad (8)$$

or for a finite length sequence, as shown in Figure 4,

$$\{G\} = \sum_{k=1}^M g(iT_s - kT_d) \quad (9)$$

The resulting function $\{X\}$ after resampling is equal to the low pass filtered function $\{W\}$, multiplied by the resampling sequence $\{G\}$, shown in Figure 4, which can be expressed as,

$$\{X\} = \{W\} \{G\} = \sum_{k=1}^M w(iT_s) g(iT_s - kT_d), \quad (10)$$

which results in a sequence,

$$x(kT_d) = c(kT_d) + jd(kT_d), \quad k=1 \dots M \quad (11)$$

The new sampling frequency is f_d , with a period between samples of T_d . To avoid the need for interpolation, M should be an integer factor of N . The analytic signal $\{X\}$ can now be enveloped to obtain the desired function where,

$$|x(kT_d)| = \sqrt{c^2(kT_d) + d^2(kT_d)}, \quad k=1 \dots M \quad (12)$$

The transform of the demodulated signal $\{X\}$ can be reshifted in frequency to obtain the high resolution frequency response if desired. However, for the analysis of the high frequency resonant modulation this is not required. The resifting of the frequency of the signal in the time domain does not affect the envelope of the demodulate $\{X\}$ but only the phase.

The frequency spectrum of the envelope function $|x(kT_d)|$ can now be computed to determine the presence of any characteristic bearing frequency components as shown in Figure 5.

The complete process of computing the envelope of the modulated bearing vibration signal is shown in Figure 6 and can be compared to the standard analogue method of computing the envelope of a band pass filtered signal shown in Figure 7.

3. EXPERIMENTAL VERIFICATION

The above method of generating the envelope of the modulation of the bearing vibration signal has been successfully implemented and used to analyse the vibration signature measured from a rolling element bearing with an implanted fault in the outer race.

3.1 Bearing Vibration Test Rig.

The experimental bearing vibration test arrangement is shown in Figure 8.

The tested rolling element bearing was located on a chuck, flexibly coupled to a 40mm diameter shaft supported by a single row spherical roller bearing and a double row ball bearing 180mm apart. The shaft was also flexibly coupled to a 0.5 HP DC motor and controlled by a Servomex controller. The calibrated thrust load was applied to the test bearing through a cantilever weight system as shown in the diagram. The principal dimensions of the taper roller bearing (NSK/NTN 30204) used in the test, are shown in Figure 9. The outer race was pressed into a bearing housing which contained a small Bruel and Kjaer accelerometer type 8309, mounted in the radial direction. The fault implanted into the outer race of the rolling element bearing consisted of a fine scribed line, as shown in Figure 10, scratched across the full width of the race surface. The width of the damage was measured to be 0.17mm.

The test bearing with the implanted fault was run in the bearing test rig at 2000 rpm with a thrust load of 295 N. The measured vibration signature was signal conditioned using a Bruel and Kjaer selectable gain and anti-aliasing low pass charge amplifier type 2635. With the low pass filter cut-off set to 30 kHz, the vibration signature was digitised at 116.2 kHz using a Metrabyte data acquisition card in an IBM compatible personal computer.

3.2 Experimental Results

A short section (10 msec) of the measured vibration signal with the bearing fault is shown in Figure 11. The two large bursts of vibration are the result of the rollers rotating past the defective outer race, the time spacing corresponding to the rolling element pass frequency in the

outer race, REPFO. The frequency response of this signal is shown in Figure 12, where the first four structural resonant modes of the bearing are evident.

The fourth resonant mode occurring at 32.5 kHz, was chosen for the verification of the new complex demodulation technique. Twenty thousand data points were digitised at the 116.2 kHz sampling rate (0.172 sec, 5.7 shaft revolutions) using the IBM pc. The data were then frequency shifted in the time domain so the resonant frequency was centred on the origin. A low pass digital filter with a cut-off at 1.1 kHz was then used to remove the unwanted frequency components which creates the analytic signal. These data were then decimated in time by resampling at 10 kHz. The envelope of the bearing vibration around the 32.5 kHz resonant mode was then computed and is shown in Figure 13. The repetitive impacts can be clearly seen in the demodulated envelope from the fourth structural mode, the repetition rate being equal to the REPFO.

The frequency spectrum of the envelope was then computed using a fast Fourier transform and the result is shown in Figure 14 with the first seven harmonics of the rolling element pass frequency of the outer race clearly visible, confirming the defect position as being on the outer race. The other resonant modes of the bearing were also found to give similar results to those given above.

3.3 Discussion

This memorandum has developed a theoretical basis for computing the high frequency resonant response, in the digital domain, using complex demodulation of a structural resonance. This technique is notable in that the envelope of the narrow frequency band around the structural resonance, is obtained without transforming the time record to the frequency domain.

The experimental results verify the effectiveness of the digital demodulation technique. The characteristic defect frequency was visible both in the envelope and the resulting spectrum. The results confirm that the repetitive impacts which occur when defects appear on bearing elements will cause modulation around a number of structural resonances and over a wide frequency range.

4. CONCLUSIONS

This paper has detailed a new method of obtaining the narrow band envelope modulation of bearing resonances. Formerly, the envelope modulation has been obtained by using an analogue band pass filter, centred on a structural resonance, and enveloping before digitising and computing the frequency spectrum. The method presented and verified in this paper involves demodulating the bearing resonant response by first digitising, then frequency shifting and

low pass filtering, all in the time domain, to obtain an analytic signal from whose envelope the frequency spectrum is obtained.

The notable points regarding this technique are as follows;

1. The method operates on the digital signal, analogue enveloping is not used.
2. The demodulation is performed wholly in the time domain, no Fourier transform is required to perform the demodulation.
3. A simple low pass filter operation is used instead of the previous bandpass filter.
4. Any structural resonance can be selected by a software change of the frequency shift operation.

5. ACKNOWLEDGEMENTS

The author acknowledges the provision and use of the bearing vibration test rig in the Department of Mechanical Engineering, University of Western Australia.

6. REFERENCES

1. Mathew J., Machine condition monitoring using vibration analysis. Acoustics Australia Vol. 15, 1987 pp 7-13.
2. Alfredson R.J. and Mathews J., Time domain methods for monitoring the condition of rolling element bearings. Transactions of the Institution of Engineers, Australia, Vol. ME10, 2, July 1985, pp 102-107.
3. Alfredson R.J. and Mathews J., Frequency domain methods for monitoring the condition of rolling element bearings. Transactions of the Institution of Engineers, Australia, Vol. ME10, 2, July 1985, pp 108-112.
4. Swansson N.S. and Favaloro S.C., Application of vibration analysis to the condition monitoring of rolling element bearings. Department of Defence, Aeronautical Research Laboratory, Melbourne. Aero Propulsion Report 163, 1984.
5. Kim P.Y., A review of rolling element bearing health monitoring II:- Preliminary test results on current technologies. Proceedings of Annual meeting, Machinery monitoring and analysis, New Orleans, Louisiana, USA, June 26-28 1984, Vibration Institute pp 127-137.

6. Darlow M.S., Badgley R.H. and Hogg G.W., Application of high-frequency resonance techniques for bearing diagnostics in helicopter gearboxes. U.S. Army Air Mobility Research and Development Laboratory Technical Report, USAAMRDL-TR-74-77, 1974.
7. Board D.B., Incipient failure detection for helicopter drive trains. Presented at the AIAA/SAE 13th Propulsion Conference, Orlando, Florida, July 11-13, 1977.
8. Elbestawi M.A. and Tait H.J., A comparative study of vibration monitoring techniques for rolling element bearings. International Modal Analysis Conference III, 1985, pp 1510-1517.
9. Prashad H., Ghosh M. and Biswas S., Diagnostic monitoring of rolling element bearings by high-frequency resonance technique. ASLE Transactions Vol. 28, 4, 1984, pp 439-448.
10. McFadden P.D., Advances in the vibration monitoring of gears and rolling element bearings. Institute of Engineers / Royal Aeronautical Society, Joint Symposium on the Influence of Aviation on Engineering, Melbourne, Australia, August 8-9, 1985, pp 27-32.
11. McFadden P.D. and Smith J.D., Vibration monitoring of rolling element bearings by the high frequency resonance technique - a review. Tribology International Vol. 17, 1, February 1984, pp 3-10.
12. Bingham C., Godfrey M.D. and Tukey J.W., Modern techniques of power spectrum estimation. IEEE Transactions on Audio and Electroacoustics, Vol. 15, 2, June 1967, pp 56-66.
13. Childers D.G. and Pao M., Complex demodulation for transient wavelet detection and extraction. IEEE Transactions on Audio and Electroacoustics, Vol. 20, 4, October 1972, pp 295-308.
14. Bell D., An enveloping technique for the detection and diagnosis of incipient faults in rolling element bearings. Vibration analysis to improve reliability and reduce failure. Proceedings of the Design Automation Conference. Cincinnati, OHIO, Sept. 10 -13, 1985, pp 65-69.
15. Kim Y., Cheung W.S. and Kwak Y.K., Complex envelope of the vibration signature of ball bearing system and its application to fault detection. The 6th International Congress on Experimental Mechanics, Portland, Oregon, June 1988, pp 1067-1071.
16. Chivers P. and Gadd P., Monitoring of rolling element bearings using vibration analysis techniques. NGA8T 6638 Feasibility Study, June 1986.




FIGURE 1. TWO SIDED SPECTRUM FROM A ROLLING ELEMENT BEARING.




FIGURE 2. TWO SIDED SPECTRUM, FREQUENCY SHIFTED BY $-f_o$, TO CENTRE THE STRUCTURAL RESONANCE AROUND THE ORIGIN.




FIGURE 3. RESULTING SPECTRUM AFTER LOW PASS DIGITAL FILTERING THE TIME SIGNAL AT FREQUENCY $\pm f_a$.




FIGURE 4. DECIMATION OF ANALYTIC SIGNAL WITH UNIT SAMPLING SEQUENCE





FIGURE 5. THE ENVELOPE OF THE BANDPASS FILTERED ANALYTIC TIME SIGNAL AND THE RESULTING FREQUENCY SPECTRUM.




FIG 6. COMPLEX DEMODULATION TO COMPUTE THE ENVELOPE OF THE BEARING VIBRATION SIGNAL




FIG 7. THE HIGH FREQUENCY RESONANCE TECHNIQUE USING AN ANALOGUE ENVELOPE CIRCUIT





FIGURE 8. SCHEMATIC DIAGRAM OF THE BEARING RIG SHOWING THE TEST BEARING ARRANGEMENT



Pitch diameter 34 mm

Roller diameter 6 mm

Contact angle 12.96°

Number of rollers 15

All dimensions in mm

FIGURE 9. SCHEMATIC DIAGRAM OF THE TESTED ROLLING ELEMENT BEARING.




FIGURE 10. SURFACE PROFILE OF THE TEST BEARING ACROSS THE LINE DEFECT




FIGURE 11. ANALOGUE BEARING VIBRATION SIGNAL WITH A LINE DEFECT IN THE OUTER RACE.




FIGURE 12. HIGH FREQUENCY STRUCTURAL RESPONSE MEASURED FROM THE TEST BEARING SHOWING FOUR BEARING RESONANCES.




FIGURE 13. ENVELOPE OF THE DEMODULATED BEARING VIBRATION SIGNAL FROM THE 32.5 kHz RESONANCE.




FIGURE 14. ENVELOPE SPECTRUM FROM THE 32.5 kHz RESONANCE MODE SHOWING THE ROLLING ELEMENT PASS FREQUENCY ON THE OUTER RACE.

DISTRIBUTION

AUSTRALIA

Department of Defence

Defence Central

Chief Defence Scientist
FAS, Science Corporate Management (shared copy)
FAS Science Policy (shared copy)
Director, Departmental Publications
Counsellor, Defence Science, London (Doc Data Sheet Only)
Counsellor, Defence Science, Washington (Doc Data Sheet Only)
SA to the Thailand Military R and D Centre (Doc Data sheet only)
SA to the D R C (Kuala Lumpur) Doc Data sheet only)
OIC TRS, Defence Central Library
Document Exchange Centre, DISB (18 copies)
Joint Intelligence Organisation
Library H Block, Victoria Barracks, Melbourne
Director General - Army Development (NSO) (4 copies)
Defence Industry and Materiel Policy, FAS

Aeronautical Research Laboratory

Director
Library
Chief - Flight Mechanics and Propulsion Division
Head - Propulsion Branch
Branch File - Propulsion
Author: I.M. Howard

Materials Research Laboratory

Director/Library

Defence Science & Technology Organisation - Salisbury

Library

WSRL

Maritime Systems Division (Sydney)

Navy Office

Navy Scientific Adviser (3 copies Doc Data sheet)
Aircraft Maintenance and Flight Trials Unit
RAN Tactical School, Library
Director of Naval Aircraft Engineering
Director of Naval Air Warfare
Superintendent, Aircraft Maintenance and Repair
Director of Naval Ship Design

Army Office

Scientific Adviser - Army (Doc Data sheet only)
Engineering Development Establishment Library
US Army Research, Development and Standardisation Group

Air Force Office

Air Force Scientific Adviser (Doc Data sheet only)
Aircraft Research and Development Unit
Scientific Flight Group
Library
Engineering Division Library
Director General Aircraft Engineering - Air Force
Director General Operational Requirements - Air Force
HQ Air Command (SMAINTSO)
HQ Support Command (SLENGO)

Department of Administrative Services

Bureau of Meteorology, Library

Department of Transport & Communication

Library

Statutory and State Authorities and Industry

Aero-Space Technologies Australia, Manager/Librarian (2 copies)
Ansett Airlines of Australia, Library
Australian Airlines, Library
Qantas Airways Limited
Civil Aviation Authority
Hawker de Havilland Aust Pty Ltd, Victoria, Library
Hawker de Havilland Aust Pty Ltd, Bankstown, Library
Rolls Royce of Australia Pty Ltd, Manager
Australian Nuclear Science and Technology Organisation
Gas & Fuel Corporation of Vic., Manager Scientific Services
SEC of Vic., Herman Research Laboratory, Library
Ampol Petroleum (Vic) Pty Ltd, Lubricant Sales & Service Mgr
Australian Coal Industry Research Labs Ltd, Director
BHP, Melbourne Research Laboratories
BP Australia Ltd, Library

Universities and Colleges

Adelaide

Barr Smith Library
Professor Mechanical Engineering

Flinders

Library

LaTrobe

Library

Melbourne
Engineering Library

Monash
Hargrave Library
Head Mechanical Engineering

Newcastle
Library

New England
Library

Sydney
Engineering Library

NSW
Physical Sciences Library
Professor R.A.A. Bryant, Mechanical Engineering
Library, Australian Defence Force Academy

Queensland
Library

Tasmania
Engineering Library

Western Australia
Library
Professor B.J. Stone, Mechanical Engineering

RMIT
Library

University College of the Northern Territory
Library

SPARES (10 COPIES)

TOTAL (110) COPIES

DOCUMENT CONTROL DATA

PAGE CLASSIFICATION
UNCLASSIFIED

PRIVACY MARKING

1a. AR NUMBER AR-006-058	1b. ESTABLISHMENT NUMBER ARL-PROP-TM-468	2. DOCUMENT DATE OCTOBER 1989	3. TASK NUMBER 89/089
4. TITLE COMPLEX DEMODULATION FOR BEARING FAULT DETECTION		5. SECURITY CLASSIFICATION (PLACE APPROPRIATE CLASSIFICATION IN BOX(S) IE. SECRET (S), CONF. (C), RESTRICTED (R), UNCLASSIFIED (U)). <div style="display: flex; justify-content: space-around;"> <div style="border: 1px solid black; padding: 2px; text-align: center;">U</div> <div style="border: 1px solid black; padding: 2px; text-align: center;">U</div> <div style="border: 1px solid black; padding: 2px; text-align: center;">U</div> </div> DOCUMENT TITLE ABSTRACT	6. NO. PAGES 22 7. NO. REFS. 16
8. AUTHOR(S) I.M. HOWARD		9. DOWNGRADING/DELIMITING INSTRUCTIONS NOT APPLICABLE	
10. CORPORATE AUTHOR AND ADDRESS AERONAUTICAL RESEARCH LABORATORY P.O. BOX 4331, MELBOURNE VIC 3001		11. OFFICE/POSITION RESPONSIBLE FOR: SPONSOR _____ DSTO SECURITY _____ DOWNGRADING _____ APPROVAL _____	
12. SECONDARY DISTRIBUTION (OF THIS DOCUMENT) Approved for public release			
OVERSEAS ENQUIRIES OUTSIDE STATED LIMITATIONS SHOULD BE REFERRED THROUGH ASD - DEFENCE INFORMATION SERVICES BRANCH, DEPARTMENT OF DEFENCE, CAMPBELL PARK, ACT 2601			
13a. THIS DOCUMENT MAY BE ANNOUNCED IN CATALOGUES AND AWARENESS SERVICES AVAILABLE TO... Unlimited			
13b. CITATION FOR OTHER PURPOSES (IE. CASUAL ANNOUNCEMENT) MAY BE <input checked="" type="checkbox"/> UNRESTRICTED OR <input type="checkbox"/> AS FOR 13a.			
14. DESCRIPTORS Vibration tests Demodulation Bearing stress Resonant frequency		15. DRDA SUBJECT CATEGORIES 0046E	
16. ABSTRACT Vibration analysis using the high frequency resonance technique has been used successfully to detect incipient failure in rolling element bearings. This memo outlines a new method of obtaining the demodulated narrow band envelope of a bearing vibration signal from the high frequency resonant response. Previous techniques have used an analogue envelope where the raw analogue signal is bandpass filtered and enveloped before digitising. The method outlined in this document first digitises the vibration signal, performs a complex demodulation operation, then computes the envelope followed by its spectrum. Fault repetition frequencies can be identified in the demodulated spectrum of the high frequency resonant response.			

PAGE CLASSIFICATION
UNCLASSIFIED

PRIVACY MARKING

THIS PAGE IS TO BE USED TO RECORD INFORMATION WHICH IS REQUIRED BY THE ESTABLISHMENT FOR ITS OWN USE BUT WHICH WILL NOT BE ADDED TO THE DISTIS DATA UNLESS SPECIFICALLY REQUESTED.

16. ABSTRACT (CONT).

17. IMPRINT

AERONAUTICAL RESEARCH LABORATORY, MELBOURNE

18. DOCUMENT SERIES AND NUMBER

PROPULSION
TECHNICAL MEMORANDUM 468

19. COST CODE

41 4140

20. TYPE OR REPORT AND PERIOD COVERED

21. COMPUTER PROGRAMS USED

22. ESTABLISHMENT FILE REF.(S)

23. ADDITIONAL INFORMATION (AS REQUIRED)